

# **IBU(Ka) Series**

Ka-Band, Single-Range, Single & Multi-Channel, Rack Mount Block UpConverters



### High Grade Single & Multi-Channel UpConverter Products;

IBU1970	L-Band (950-1450MHz) to Ka-Band (19.70-20.20GHz)
IBU2750	L-Band (950-1950MHz) to Ka-Band (27.50-28.50GHz)
IBU2830	L-Band (950-1750MHz) to Ka-Band (28.30-29.10GHz)
IBU2850	L-Band (950-1950MHz) to Ka-Band (28.50-29.50GHz)
IBU2900	L-Band (950-1950MHz) to Ka-Band (29.00-30.00GHz)
IBU2960	L-Band (950-1550MHz) to Ka-Band (29.60-30.20GHz)
IBU3100	L-Band (950-1950MHz) to Ka-Band (30.00-31.00GHz)

For other non-standard frequency requirements and multi-channel units, please contact the factory. For equivalent units with full user interface, remote control and digital attenuation, please see IBUH(Ka) series datasheet. For equivalent remote mount units, please see PBU(Ka) series datasheet.

The 19-inch 1U rack mounted IBU(Ka) series of block frequency up converter units from Peak Communications are designed to take the output of an up converter or modem at L-Band and produce an output at SHF.

The IBU(Ka) series of units are mains powered and are constructed of high grade components to give the ultimate performance.

For 1+1 & 2+1 redundancy the IBU(Ka) series are offered with the RCU100/ RCU200 & RCUH100/ RCUH200 series redundancy controllers. For N+1 the RCU1001(Ka) series is offered.

#### The unit has a highly stable internal reference source and will automatically detect and lock to an external 10MHz signal, when applied.

#### **Peak Features**

- $\mathbb{M}$ High stability, low ripple and excellent phase noise, using PDRO technology  $\mathbb{M}$ 10MHz external reference fitted as standard with automatic internal reference back-up  $\mathbb{M}$ Fully compatible with RCU100/ RCU200 & RCUH100/ RCUH200 series 1+1/ 2+1 redundancy controllers and RCU1001(Ka) series for N+1 redundancy units  $\mathbb{M}$ L-Band monitor and fibre optic L-Band interface options available
- $\square$ 
  - Available in dual, triple & quad-channel versions



## IBU(Ka) series - Typical Specification

	Turnical Creation	External Reference Input (with automatic detection)		
IBU(Ka) serie	es - Typical Specification	Frequency	10MHz (5MHz factory settable)	
		Connector	BNC (f), $50\Omega$	
SHF Output		Level	0dBm ±5dB	
Frequency	19.7-20.2GHz	Required phase noise	better than 50dBc/Hz of output phase noise	
IBU1970 IBU2750	27.5-28.5GHz	Locking delay	<2 minutes to stabilise from cold	
IBU2750 IBU2830	28.3-29.1GHz	Internal Back-up Refere	nce Stability	
		Allan deviation	5 x 10 <sup>-11</sup> over 1s	
IBU2850	28.5-29.5GHz	Ageing	<5 x 10 <sup>-9</sup> per day, <5 x 10 <sup>-7</sup> per year	
IBU2900	29.0-30.0GHz	Temp stability	<5 x 10 <sup>-8</sup> over 0 to 50°C	
IBU3020 IBU3100	29.6-30.2GHz	High stability (Option	8)	
Connector	30.0-31.0GHz K-Type (f), 50Ω or 2.92mm (f)	Allan deviation	3 x 10 <sup>-12</sup> over 1s	
	annel version, multiple connectors are provided	Ageing	<2 x 10 <sup>-10</sup> per day, <2 x 10 <sup>-8</sup> per year	
Return loss	18dB	Temp stability	<3 x 10 <sup>-9</sup> over 0 to 50°C	
1dB GCP	+8dBm	. ,		
	FOUDIN	Mechanical		
L-Band Input		Width	19" standard rack mountable	
Frequency	950 up to 2050MHz, model dependant	Height	1U (1.75")	
Connector	SMA (f), 50Ω	Depth	~400mm (15.7"), plus connectors	
Option 1b;	N-Type (f), 50Ω		annel versions, a longer ~534mm (21") chassis	
Note; for multi-cha	annel version, multiple connectors are provided	and the second	depending upon options selected.	
Return loss	18dB	Construction	Aluminium chassis	
		Weight	3.5-6kgs (8-13lbs) approx., unit & option	
Transfer Characteristic			dependent	
Conversion gain	17dB ±1dB at band centre	Environmental		
Gain stability	$\pm 0.75$ dB from 0 to 50°C	Operating temp	0°C to +50°C	
Gain flatness	±1dB full band (±1.5dB for bandwidths ≥800MHz)	EMC	EN 55022, part B & EN 50082-1	
	±0.5dB across any 40MHz in-band	Safety	EN 60950	
LO frequency	dependant on model	Caloty	21100000	
Manual L-Band Attenua	ation (Option 10)	Power Supply		
Attenuation range	30dB nominal	Voltage	90-264VAC	
Control	Continuously variable from front panel	Frequency	47-63Hz	
	e gain flatness performance	Power	50 Watts max.	
_	<b>o</b>	Option 7;		
RF Performance			power supply configuration with separate prime	
LO phase noise	-45dBc/Hz at 10Hz		power inputs	
(typical with good	-65dBc/Hz at 100Hz	Control System Interfa	<b>60</b>	
phase noise	-95dBc/Hz at 1kHz	Alarms	LO lock failure	
ext. 10MHz ref)	-100dBc/Hz at 10kHz	Alainis	PSU failure	
	-100dBc/Hz at 100kHz		Amplifier failure	
	-115dBc/Hz at 1MHz			
Spurious	<-70dBm (in-band non-carrier related)	<b>Options</b>		
Net a ord be me as to	<-65dBc (in-band carrier related)	options		
	c of IF (2xIF) at -50dBc@0dBm output, if in-band	1b) N-Type (f) L-Band	interface connection	
LO leakage	-70dBm (always out of band)		onitor on rear panel (SMA)	
3rd order intercept	>+18dBm		onitor on front panel (SMA)	
SHF & L-Band Monitor	(Option 2)	,	interface connection	
Connector	(0)	7) Redundant power supplies		
Option 2a;	L-Band monitor, SMA (f), 50 $\Omega$ on rear panel	<ul><li>8) High stability internal reference option</li></ul>		
Option 2b;	L-Band monitor, SMA (f), $50\Omega$ on front panel	, 0 ,	ttenuator, 0-30dB, at L-band	
	nnector types please consult the factory		options can modify the typical specification, for	
Level	-20dBc ±3dB	details please consu		
-				
Deermonster				

## Rear panel view (sample)





Peak Communications reserves the right to alter the specifications of this equipment without prior notice. IBU(Ka)series-290823. Peak Communications Ltd., Unit 1, The Woodvale Centre, Woodvale Road, Brighouse, West Yorkshire, HD6 4AB, U.K. Tel; +44 (0)1484 714200 Email; <u>sales@peakcom.co.uk</u> Web; <u>www.peakcom.co.uk</u>